



**ABSTRACT**

This document provides the register bit values for the one-time programmable (OTP) bits of the orderable part number LP875230CRNFRQ1.

**Table of Contents**

**1 Introduction**..... 1  
**2 Register Bits Loaded From OTP Memory**..... 3

**List of Tables**

Table 1-1. Main OTP Settings for Power Rails..... 1  
 Table 2-1. Summary of Registers Bits..... 3

**Trademarks**

All trademarks are the property of their respective owners.

**1 Introduction**

This technical reference manual can be used as a reference for the LP875230C-Q1 default register bits after OTP memory download. This technical reference manual does not provide information about the electrical characteristics, external components, package, or the functionality of the device. For this information and the full register map, refer to the [LP8752x-Q1 Four-Phase 10-A Buck Converter With Integrated Switches data sheet](#)

[Table 1-1](#) lists the main OTP settings for power rails. [Table 2-1](#) lists the register bits loaded from OTP memory.

**Table 1-1. Main OTP Settings for Power Rails**

| Description                      |  | Bit Name                                    | LP875230CRNFRQ1 Value |
|----------------------------------|--|---|-----------------------|
| Device identification            | OTP configuration                            | OTP_ID                                      | 7Eh                   |
| BUCK0, BUCK1 (2-phase operation) | Output voltage                               | BUCK0_VSET                                  | 850 mV                |
|                                  | Enable, EN pin, or I <sup>2</sup> C register | EN_BUCK0, EN_PIN_CTRL0, BUCK0_EN_PIN_SELECT | EN1                   |
|                                  | Force PWM                                    | BUCK0_FPWM                                  | Yes                   |
|                                  | Force multiphase                             | BUCK0_FPWM_MP                               | Yes                   |
|                                  | Peak current limit per phase                 | N/A   | 4 A                   |
|                                  | Maximum load current                         | N/A   | 6 A                   |
|                                  | Slew rate                                    | N/A   | 3.8 mV/μs             |
| BUCK2                            | Output voltage                               | BUCK2_VSET                                  | 1100 mV               |
|                                  | Enable, EN pin, or I <sup>2</sup> C register | EN_BUCK2, EN_PIN_CTRL2, BUCK2_EN_PIN_SELECT | EN1                   |
|                                  | Force PWM                                    | BUCK2_FPWM                                  | Yes                   |
|                                  | Peak current limit                           | N/A   | 3 A                   |
|                                  | Maximum load current                         | N/A   | 2 A                   |
|                                  | Slew rate                                    | N/A   | 3.8 mV/μs             |

**Table 1-1. Main OTP Settings for Power Rails (continued)**

| Description              |  | Bit Name                                       | LP875230CRNFRQ1 Value |
|--------------------------|--|--|-----------------------|
| BUCK3                    | Output voltage                               | BUCK3_VSET                                     | 1800 mV               |
|                          | Enable, EN pin, or I <sup>2</sup> C register | EN_BUCK3, EN_PIN_CTRL3,<br>BUCK3_EN_PIN_SELECT | EN1                   |
|                          | Force PWM                                    | BUCK3_FPWM                                     | Yes                   |
|                          | Peak current limit                           | N/A  | 3 A                   |
|                          | Maximum load current                         | N/A  | 2 A                   |
|                          | Slew rate                                    | N/A  | 3.8 mV/μs             |
| Switching frequency      |  | N/A  | 2 MHz                 |
| I <sup>2</sup> C address |  | N/A  | 61h                   |

**Note**

The maximum total output capacitance (local + POL) per phase (BUCK0, BUCK1, BUCK2, and BUCK3) depends on the slew rate setting. Check the data sheet for the allowed capacitance value.

## 2 Register Bits Loaded From OTP Memory

Table 2-1 lists the register bit values loaded from the OTP memory during device start-up.

**Table 2-1. Summary of Registers Bits**

| Address | Register Name | Bit                       | LP875230CRNFRQ1 Value |
|---------|---------------|---------------------------|-----------------------|
| 0x01    | OTP_REV       | OTP_ID[7:0]               | 7Eh                   |
| 0x02    | BUCK0_CTRL1   | EN_BUCK0                  | 1h                    |
| 0x02    | BUCK0_CTRL1   | EN_PIN_CTRL0              | 1h                    |
| 0x02    | BUCK0_CTRL1   | BUCK0_EN_PIN_SELECT[1:0]  | 0h                    |
| 0x02    | BUCK0_CTRL1   | BUCK0_FPWM                | 1h                    |
| 0x02    | BUCK0_CTRL1   | BUCK0_FPWM_MP             | 1h                    |
| 0x04    | BUCK1_CTRL1   | EN_BUCK1                  | 1h                    |
| 0x04    | BUCK1_CTRL1   | EN_PIN_CTRL1              | 1h                    |
| 0x04    | BUCK1_CTRL1   | BUCK1_EN_PIN_SELECT[1:0]  | 0h                    |
| 0x04    | BUCK1_CTRL1   | BUCK1_FPWM                | 1h                    |
| 0x06    | BUCK2_CTRL1   | EN_BUCK2                  | 1h                    |
| 0x06    | BUCK2_CTRL1   | EN_PIN_CTRL2              | 1h                    |
| 0x06    | BUCK2_CTRL1   | BUCK2_EN_PIN_SELECT[1:0]  | 0h                    |
| 0x06    | BUCK2_CTRL1   | BUCK2_FPWM                | 1h                    |
| 0x06    | BUCK2_CTRL1   | BUCK2_FPWM_MP             | 0h                    |
| 0x08    | BUCK3_CTRL1   | EN_BUCK3                  | 1h                    |
| 0x08    | BUCK3_CTRL1   | EN_PIN_CTRL3              | 1h                    |
| 0x08    | BUCK3_CTRL1   | BUCK3_EN_PIN_SELECT[1:0]  | 0h                    |
| 0x08    | BUCK3_CTRL1   | BUCK3_FPWM                | 1h                    |
| 0x0A    | BUCK0_VOUT    | BUCK0_VSET[7:0]           | 2Fh                   |
| 0x0C    | BUCK1_VOUT    | BUCK1_VSET[7:0]           | 2Fh                   |
| 0x0E    | BUCK2_VOUT    | BUCK2_VSET[7:0]           | 61h                   |
| 0x10    | BUCK3_VOUT    | BUCK3_VSET[7:0]           | B1h                   |
| 0x12    | BUCK0_DELAY   | BUCK0_SHUTDOWN_DELAY[3:0] | 5h                    |
| 0x12    | BUCK0_DELAY   | BUCK0_STARTUP_DELAY[3:0]  | 0h                    |
| 0x13    | BUCK1_DELAY   | BUCK1_SHUTDOWN_DELAY[3:0] | 5h                    |
| 0x13    | BUCK1_DELAY   | BUCK1_STARTUP_DELAY[3:0]  | 0h                    |
| 0x14    | BUCK2_DELAY   | BUCK2_SHUTDOWN_DELAY[3:0] | 1h                    |
| 0x14    | BUCK2_DELAY   | BUCK2_STARTUP_DELAY[3:0]  | 5h                    |
| 0x15    | BUCK3_DELAY   | BUCK3_SHUTDOWN_DELAY[3:0] | 2h                    |
| 0x15    | BUCK3_DELAY   | BUCK3_STARTUP_DELAY[3:0]  | 3h                    |
| 0x16    | GPIO2_DELAY   | GPIO2_SHUTDOWN_DELAY[3:0] | 0h                    |
| 0x16    | GPIO2_DELAY   | GPIO2_STARTUP_DELAY[3:0]  | 7h                    |
| 0x17    | GPIO3_DELAY   | GPIO3_SHUTDOWN_DELAY[3:0] | 5h                    |
| 0x17    | GPIO3_DELAY   | GPIO3_STARTUP_DELAY[3:0]  | 0h                    |
| 0x19    | CONFIG        | DOUBLE_DELAY              | 0h                    |
| 0x19    | CONFIG        | CLKIN_PD                  | 1h                    |
| 0x19    | CONFIG        | EN4_PD                    | 0h                    |
| 0x19    | CONFIG        | EN3_PD                    | 1h                    |
| 0x19    | CONFIG        | TDIE_WARN_LEVEL           | 1h                    |
| 0x19    | CONFIG        | EN2_PD                    | 1h                    |
| 0x19    | CONFIG        | EN1_PD                    | 1h                    |
| 0x21    | TOP_MASK1     | GPIO_MASK                 | 1h                    |
| 0x21    | TOP_MASK1     | SYNC_CLK_MASK             | 1h                    |
| 0x21    | TOP_MASK1     | TDIE_WARN_MASK            | 0h                    |
| 0x21    | TOP_MASK1     | I_LOAD_READY_MASK         | 1h                    |
| 0x22    | TOP_MASK2     | RESET_REG_MASK            | 1h                    |
| 0x23    | BUCK_0_1_MASK | BUCK1_PG_MASK             | 1h                    |

**Table 2-1. Summary of Registers Bits (continued)**

| Address | Register Name | Bit                 | LP875230CRNFRQ1 Value |
|---------|---------------|---------------------|-----------------------|
| 0x23    | BUCK_0_1_MASK | BUCK1_ILIM_MASK     | 1h                    |
| 0x23    | BUCK_0_1_MASK | BUCK0_PG_MASK       | 1h                    |
| 0x23    | BUCK_0_1_MASK | BUCK0_ILIM_MASK     | 1h                    |
| 0x24    | BUCK_2_3_MASK | BUCK3_PG_MASK       | 1h                    |
| 0x24    | BUCK_2_3_MASK | BUCK3_ILIM_MASK     | 1h                    |
| 0x24    | BUCK_2_3_MASK | BUCK2_PG_MASK       | 1h                    |
| 0x24    | BUCK_2_3_MASK | BUCK2_ILIM_MASK     | 1h                    |
| 0x28    | PGOOD_CTRL1   | PG3_SEL[1:0]        | 1h                    |
| 0x28    | PGOOD_CTRL1   | PG2_SEL[1:0]        | 1h                    |
| 0x28    | PGOOD_CTRL1   | PG1_SEL[1:0]        | 0h                    |
| 0x28    | PGOOD_CTRL1   | PG0_SEL[1:0]        | 1h                    |
| 0x29    | PGOOD_CTRL2   | HALF_DELAY          | 1h                    |
| 0x29    | PGOOD_CTRL2   | EN_PG0_NINT         | 0h                    |
| 0x29    | PGOOD_CTRL2   | PGOOD_SET_DELAY     | 0h                    |
| 0x29    | PGOOD_CTRL2   | EN_PGFLT_STAT       | 0h                    |
| 0x29    | PGOOD_CTRL2   | PGOOD_WINDOW        | 1h                    |
| 0x29    | PGOOD_CTRL2   | PGOOD_OD            | 1h                    |
| 0x29    | PGOOD_CTRL2   | PGOOD_POL           | 0h                    |
| 0x2B    | PLL_CTRL      | PLL_MODE[1:0]       | 0h                    |
| 0x2B    | PLL_CTRL      | EXT_CLK_FREQ[4:0]   | 1h                    |
| 0x2C    | PIN_FUNCTION  | EN_SPREAD_SPEC      | 1h                    |
| 0x2C    | PIN_FUNCTION  | EN_PIN_CTRL_GPIO3   | 1h                    |
| 0x2C    | PIN_FUNCTION  | EN_PIN_SELECT_GPIO3 | 0h                    |
| 0x2C    | PIN_FUNCTION  | EN_PIN_CTRL_GPIO2   | 1h                    |
| 0x2C    | PIN_FUNCTION  | EN_PIN_SELECT_GPIO2 | 0h                    |
| 0x2C    | PIN_FUNCTION  | GPIO3_SEL           | 1h                    |
| 0x2C    | PIN_FUNCTION  | GPIO2_SEL           | 1h                    |
| 0x2C    | PIN_FUNCTION  | GPIO1_SEL           | 0h                    |
| 0x2D    | GPIO_CONFIG   | GPIO3_OD            | 0h                    |
| 0x2D    | GPIO_CONFIG   | GPIO2_OD            | 0h                    |
| 0x2D    | GPIO_CONFIG   | GPIO1_OD            | 0h                    |
| 0x2D    | GPIO_CONFIG   | GPIO3_DIR           | 1h                    |
| 0x2D    | GPIO_CONFIG   | GPIO2_DIR           | 1h                    |
| 0x2D    | GPIO_CONFIG   | GPIO1_DIR           | 0h                    |
| 0x2F    | GPIO_OUT      | GPIO3_OUT           | 1h                    |
| 0x2F    | GPIO_OUT      | GPIO2_OUT           | 1h                    |

## IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on [ti.com](http://ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2022, Texas Instruments Incorporated