

TIDA-01095 REV E1 Bill of Materials

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	!PCB1	1		TIDA-01095	Any	Printed Circuit Board	
2	C1	1	2.2uF	GRM32ER72A225KA35L	MuRata	CAP, CERM, 2.2 uF, 100 V, +/- 10%, X7R, 1210	1210
3	C2	1	2.2uF	GRM188R61C225KE15D	MuRata	CAP, CERM, 2.2 uF, 16 V, +/- 10%, X5R, 0603	0603
4	C3	1	1uF	C3225X7R2A105K200AA	TDK	CAP, CERM, 1 uF, 100 V, +/- 10%, X7R, 1210	1210
5	C4	1	1800pF	GRM188R71E182KA01D	MuRata	CAP, CERM, 1800 pF, 25 V, +/- 10%, X7R, 0603	0603
6	C5	1	0.22uF	GRM188R71E224KA88D	MuRata	CAP, CERM, 0.22 uF, 25 V, +/- 10%, X7R, 0603	0603
7	C6, C12, C20	3	10uF	GRT188C81A106ME13D	MuRata	CAP, CERM, 10 uF, 10 V, +/- 20%, X6S, AEC-Q200 Grade 2, 0603	0603
8	C7, C8, C10, C13, C19	5	0.1uF	GRM188R71E104KA01D	MuRata	CAP, CERM, 0.1 uF, 25 V, +/- 10%, X7R, 0603	0603
9	C11	1	0.47uF	CGA3E3X7R1E474K080AB	TDK	CAP, CERM, 0.47 uF, 25 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0603	0603
10	C14, C18	2	0.47uF	GRM188R70J474KA01D	MuRata	CAP, CERM, 0.47 uF, 6.3 V, +/- 10%, X7R, 0603	0603
11	C15	1	0.047uF	GRM188R70J473KA01D	MuRata	CAP, CERM, 0.047 uF, 6.3 V, +/- 10%, X7R, 0603	0603
12	C16	1	4700pF	GCM188R71H472KA37D	MuRata	CAP, CERM, 4700 pF, 50 V, +/- 10%, X7R, AEC-Q200 Grade 1, 0603	0603
13	C17	1	470pF	C0603X471K5RACTU	Kemet	CAP, CERM, 470 pF, 50 V, +/- 10%, X7R, 0603	0603
14	D1	1	100V	MBR1H100SFT3G	ON Semiconductor	Diode, Schottky, 100 V, 1 A, SOD-123FL	SOD-123FL
15	D2	1	100V	1N4148W-7-F	Diodes Inc.	Diode, Ultrafast, 100 V, 0.15 A, SOD-123	SOD-123
16	H1, H2, H3, H4	4		PMSSS 440 0025 PH	B&F Fastener Supply	MACHINE SCREW PAN PHILLIPS 4-40	Machine Screw, 4-40, 1/4"
17	H5, H6, H7, H8	4		1902E	Keystone	Standoff, Hex, 1"L #4-40 Nylon	Standoff
18	J1, J3	2		691216510002	Würth Elektronik	Receptacle, 5.08mm, 2x1, Brass, TH	Receptacle, 5.08mm, 2x1, TH
19	J2	1		SL 11 112 03G	Fischer Elektronik	Header, 2.54mm, 3x1, Gold, TH	TH, 3-Leads, Body 2.5x7.62mm, Pitch 2.54mm
20	J4	1		TSW-105-07-G-S	Samtec	Header, 100mil, 5x1, Gold, TH	5x1 Header
21	J5, J6	2		PEC10DAAN	Sullins Connector Solutions	Header, 100mil, 10x2, TH	Header, 10x2, 2.54mm, TH
22	L1	1		74435586800	Würth Elektronik	WE-HCI SMD Flat Wire High Current Inductor, Inductance = 68.0 uH	
23	Q1	1	60V	CSD18537N0Q5A	Texas Instruments	MOSFET, N-CH, 60 V, 50 A, SON 5x6mm	SON 5x6mm
24	Q2	1	60V	CSD18563Q5A	Texas Instruments	MOSFET, N-CH, 60 V, 15 A, SON 5x6mm	SON 5x6mm
25	R1	1	120k	CRCW0603120KJNEA	Vishay-Dale	RES, 120 k, 5%, 0.1 W, 0603	0603
26	R2	1	47k	CRCW060347K0JNEA	Vishay-Dale	RES, 47 k, 5%, 0.1 W, 0603	0603
27	R3	1	4.99k	CRCW06034K99FKEA	Vishay-Dale	RES, 4.99 k, 1%, 0.1 W, 0603	0603
28	R4, R10	2	100	RC0603FR-07100RL	Yageo America	RES, 100, 1%, 0.1 W, 0603	0603
29	R5	1	20.0k	CRCW060320K0FKEA	Vishay-Dale	RES, 20.0 k, 1%, 0.1 W, 0603	0603
30	R8	1	1.21Meg	CRCW06031M21FKEA	Vishay-Dale	RES, 1.21 M, 1%, 0.1 W, 0603	0603
31	R9	1	475	CRCW0603475RFKEA	Vishay-Dale	RES, 475, 1%, 0.1 W, 0603	0603
32	R11	1	10.0k	CRCW060310K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.1 W, 0603	0603
33	R12	1	0.05	CSRN2512FK50L0	Stackpole Electronics Inc	RES, 0.05, 1%, 2 W, 2512	2512
34	R13	1	5.6k	CRCW06035K60JNEA	Vishay-Dale	RES, 5.6 k, 5%, 0.1 W, 0603	0603
35	R14	1	100k	RC0603FR-07100KL	Yageo America	RES, 100 k, 1%, 0.1 W, 0603	0603
36	R15	1	866	RC0603FR-07866RL	Yageo America	RES, 866, 1%, 0.1 W, 0603	0603
37	R16	1	8.66k	RC0603FR-078K66L	Yageo America	RES, 8.66 k, 1%, 0.1 W, 0603	0603
38	R17	1	86.6k	CRCW060386K6FKEA	Vishay-Dale	RES, 86.6 k, 1%, 0.1 W, 0603	0603
39	R18	1	866k	RC0603FR-07866KL	Yageo America	RES, 866 k, 1%, 0.1 W, 0603	0603
40	R19	1	11.0k	CRCW060311K0FKEA	Vishay-Dale	RES, 11.0 k, 1%, 0.1 W, 0603	0603
41	R20	1	1.50k	RC0603FR-071K5L	Yageo America	RES, 1.50 k, 1%, 0.1 W, 0603	0603
42	R21	1	0	MCR18EZJH000	Rohm	RES, 0, 5%, 0.25 W, 1206	1206
43	TP1, TP3, TP4, TP6, TP7, TP9, TP10, TP11	8	White	5002	Keystone	Test Point, Miniature, White, TH	White Miniature Testpoint
44	U1	1		TPS92641PWPR/NOPB	Texas Instruments	Synchronous Buck Controller for Precision Dimming LED Drivers, PWP0016A	PWP0016A
45	U2	1		OPA376AIDBVR	Texas Instruments	Precision, Low Noise, Low Iq Operational Amplifier, 2.2 to 5.5 V, -40 to 125 degC, 5-pin SOT23 (DBV0005A), Green (RoHS & no Sb/Br)	DBV0005A
46	C9	0	1uF	GRM32R71H105KA01L	MuRata	CAP, CERM, 1 uF, 50 V, +/- 10%, X7R, 1210	1210
47	FID1, FID2, FID3	0		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	N/A
48	Q3	0	60V	CSD18563Q5A	Texas Instruments	MOSFET, N-CH, 60 V, 15 A, SON 5x6mm	SON 5x6mm
49	R6	0	866	RC0603FR-07866RL	Yageo America	RES, 866, 1%, 0.1 W, 0603	0603
50	R7	0	10.0k	CRCW060310K0FKEA	Vishay-Dale	RES, 10.0 k, 1%, 0.1 W, 0603	0603

IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Designer(s)") who are developing systems that incorporate TI products. TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.

TI's provision of reference designs and any other technical, applications or design advice, quality characterization, reliability data or other information or services does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such reference designs or other items.

TI reserves the right to make corrections, enhancements, improvements and other changes to its reference designs and other items.

Designer understands and agrees that Designer remains responsible for using its independent analysis, evaluation and judgment in designing Designer's systems and products, and has full and exclusive responsibility to assure the safety of its products and compliance of its products (and of all TI products used in or for such Designer's products) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to its applications, it has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any systems that include TI products, Designer will thoroughly test such systems and the functionality of such TI products as used in such systems. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

Designers are authorized to use, copy and modify any individual TI reference design only in connection with the development of end products that include the TI product(s) identified in that reference design. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of the reference design or other items described above may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS AND OTHER ITEMS DESCRIBED ABOVE ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNERS AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS AS DESCRIBED IN A TI REFERENCE DESIGN OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

TI's standard terms of sale for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>) apply to the sale of packaged integrated circuit products. Additional terms may apply to the use or sale of other types of TI products and services.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2016, Texas Instruments Incorporated